

6.0 KVA PETROL GENERATOR

FEATURES & BENEFITS

- Maximum 6.5 kVA, 230V, Smart Throttled RPM
- Inverter Type (Automatic Voltage Regulator)
- Electric & Recoil
- 14 Litre Fuel Tank, 4 Hours @ 75% load
- Silent "Suitcase" Type Version ($\pm 62 \sim 94$ dBA)
- Single Cylinder, Forced Air-Cooling, 4-stroke
- Single Phase Output
- 3-in-1 Display Meter Digital
- DC Output V-Type 12V 8.3A
- 1 x 16A Socket, 1 x 32A Socket



GENERAL DATA	
Model:	BP6500ISE
Prime Power (P.R.P):	6.0 kVA
Stand-by Power (L.T.P):	6.5 kVA
Amps:	28 A
Power Factor / COS:	1
Frequency:	50 Hz
Voltage:	230 V
Phases:	Single Phase
Engine Speed:	Smart Throttled RPM
Length:	605 mm
Width:	470 mm
Height:	560 mm
Weight:	55 kg's
Tank Capacity:	14 l

ADDITIONAL	
Running Time:	4 Hours @ 75% load
Structure Type:	Silent "Suitcase" Type
Noise Level (7m):	62 ~ 94 dBA
Auto Voltage Regulator:	Inverter Type
ISO9001 Certified:	Yes
CE Certified:	Yes
Fuel Cons. @ 100% Load:	4.0
Fuel Cons. @ 75% Load:	3.0
Fuel Cons. @ 50% Load:	2.0

ENGINE DATA	
Brand:	Genkins
Model:	LT330-VI
Type:	Single Cylinder, Forced Air-Cooling, 4-stroke
Starting System:	Electric & Recoil
Auto-Decompression:	Yes
Cubic Capacity (l):	0.327
Compression Ratio:	8.8:1
Rated Power (kW/RPM):	7.5kW
Fuel Type:	Petrol
Lube Oil:	10W-30 / SAE30
Low Pressure Alert:	N/A
Low Fuel Cut Out:	N/A

CONTROL PANEL	
Model:	3-in-1 Display Meter
Type:	Digital
Analogue Inputs:	N/A
Mains Phase Voltage:	No
Mains Line Voltage:	No

ALTERNATOR	
Model:	
Pole Number:	N/A
Excitation Mode:	

Johannesburg
011 397 7373

Pietermaritzburg
033 007 0812

Nelspruit
013 007 1753

Bloemfontein
051 001 1429